## ELECTRICAL SYMBOLS:

| | |
|---|---|
| USB WP GFCI | DUPLEX RECEPTACLE, 125V, 20A. INSTALL DEVICE WITH BOTTOM AT +16" AFF., UON. ASTERISK "*" = VANDALPROOF STYLE RECEPTACLE FACEPLATE. USB = 125V, 20A. USB CHARGING DUPLEX RECEPTACLE, 5.0 AMPERES CHARGING WITH ONE (1) TYPE A AND ONE (1) TYPE C USB PORTS. WP = WEATHERPROOF "WHILE-IN-USE" COVER. GFCI = GROUND FAULT CIRCUIT INTERRUPTING TYPE DEVICE. |
| * COPIER C-I C-G SUR | COPIER = COPIER OUTLET, FIELD VERIFY NEMA CONFIGURATION WITH OWNER PRIOR TO CONSTRUCTION, INSTALL DEVICE WITH BOTTOM AT +16" AFF. C-I = RECEPTACLE INDIVIDUALLY CONTROLLED BY SECURITY ELECTRONICS RELAY CABINET. C-G = RECEPTACLE GROUP CONTROLLED BY SECURITY ELECTRONICS RELAY CABINET. SUR = DEVICE TO BE SURFACE MOUNTED UON. COORDINATE EXACT LOCATION BEFORE ROUGH-IN. |
| VV | VV = DUPLEX RECEPTACLE, 125VAC, 20 A FOR FUTURE VIDEO VISITATION STATION. INSTALL SINGLE GANG BOX, PROVIDE WITH SECURITY FASTENERS ON FACEPLATE COVER U.O.N. MOUNT BOX AT +48" AFF U.O.N. |
| USB | USB CHARINGING DUPLEX RECEPTACLE, 125V, 20A. INSTALL DEVICE WITH BOTTOM AT +36" AFF., U.O.N. |
| WP | GROUND FAULT CIRCUIT INTERRUPTING TYPE RECEPTACLE, 125V, 20A. INSTALL DEVICE WITH BOTTOM AT +16" A.F.F. WP = WEATHERPROOF "WHILE-IN-USE" ENCLOSURE. |
| | DUPLEX RECEPTACLE, 125V, 20A. INSTALL DEVICE ABOVE COUNTER OR BACKSPLASH U.O.N. COORDINATE EXACT LOCATION AND HEIGHT WITH CABINET/CASEWORK SHOP DRAWING SUBMITTALS BEFORE ROUGH-IN. |
| | DUPLEX RECEPTACLE ON UNITERRUPTIBLE POWER SUPPLY CIRCUIT, 125V, 20A. INSTALL DEVICE WITH BOTTOM AT +16", A.F.F., U.O.N. RECEPTACLE TO BE COLOR "ORANGE". COORDINATE EXACT LOCATION BEFORE ROUGH-IN. |
| | DUPLEX RECEPTACLE ON UNITERRUPTIBLE POWER SUPPLY CIRCUIT, 125V, 20A. INSTALL DEVICE ABOVE COUNTER OR BACKSPLASH U.O.N. COORDINATE EXACT LOCATION AND HEIGHT WITH CABINET/CASEWORK SHOP DRAWING SUBMITTALS BEFORE ROUGH-IN. RECEPTACLE TO BE COLOR "ORANGE". |
| | DUPLEX RECEPTACLE CEILING MOUNTED 125V, 20A. REFER TO SPECIFICATIONS AND DRAWINGS FOR FURTHER DETAILS. |
| | DUPLEX RECEPTACLE CEILING MOUNTED ON UNITERRUPTIBLE POWER SUPPLY CIRCUIT 125V, 20A. REFER TO SPECIFICATIONS AND DRAWINGS FOR FURTHER DETAILS. RECEPTACLE TO BE COLOR "ORANGE". |
| | DUPLEX RECEPTACLE FLOOR BOX 125V, 20A. REFER TO SPECIFICATIONS AND DRAWINGS FOR DETAILED ELECTRICAL REQUIREMENTS. ALSO FOR COMBINATION POWER/DATA FLUSH FLOOR BOX DETIAL, REFER TO DETAIL #7 ON DRAWING E8.5. |
| | QUAD RECEPTACLE, 125V, 20A. INSTALL DEVICE WITH BOTTOM AT +16" A.F.F., U.O.N. COORDINATE EXACT LOCATION BEFORE ROUGH-IN |
| | QUAD RECEPTACLE, 125V, 20A. INSTALL DEVICE ABOVE COUNTER OR BACKSPLASH U.O.N. COORDINATE EXACT LOCATION AND HEIGHT WITH CABINET/CASEWORK SHOP DRAWING SUBMITTALS BEFORE ROUGH-IN. |
| | QUAD RECEPTACLE ON UNINTERRUPTIBLE POWER SUPPLY CIRCUIT, 125V, 20A. INSTALL DEVICE WITH BOTTOM AT +16" A.F.F., U.O.N. RECEPTACLE TO BE COLOR "ORANGE". COORDINATE EXACT LOCATION BEFORE ROUGH-IN. |
| | QUAD RECEPTACLE ON UNINTERRUPTIBLE POWER SUPPLY CIRCUIT, 125V, 20A. INSTALL DEVICE ABOVE COUNTER OR BACKSPLASH U.O.N. COORDINATE EXACT LOCATION AND HEIGHT WITH CABINET/CASEWORK SHOP DRAWING SUBMITTALS BEFORE ROUGH-IN. RECEPTACLE TO BE COLOR "ORANGE". |
| | GROUND FAULT CIRCUIT INTERRUPTING TYPE QUAD RECEPTACLE, 125V, 20A. INSTALL DEVICE WITH BOTTOM AT +16" A.F.F. COORDINATE EXACT LOCATION BEFORE ROUGH-IN. |
| | SPECIAL RECEPTACLE, REFER TO MANUFACTURER OF CORD AND PLUG EQUIPMENT FOR MATCHING NEMA-CONFIGURED RECEPTACLE REQUIREMENT. INSTALL DEVICE WITH BOTTOM AT +16" A.F.F., U.O.N. COORDINATE EXACT LOCATION BEFORE ROUGH-IN. |
| | SPECIAL RECEPTACLE ON UNINTERRUPTIBLE POWER SUPPLY CIRCUIT, REFER TO MANUFACTURER OF CORD AND PLUG EQUIPMENT FOR MATCHING NEMA-CONFIGURED RECEPTACLE REQUIREMENT. INSTALL DEVICE WITH BOTTOM AT +16" A.F.F., U.O.N. COORDINATE EXACT LOCATION BEFORE ROUGH-IN. RECEPTACLE TO BE COLOR "ORANGE". |
| J J J | JUNCTION BOX |
| R | RELAY |
| a *WP | TOGGLE SWITCH, 120/277V, 1-POLE, 20A. INSTALL DEVICE WITH CENTER AT +48" A.F.F. U.O.N. ASTERISK "*" = VANDALPROOF STYLE DEVICE FACEPLATE. WP=WEATHERPROOF ENCLOSURE, "a" INDICATES SWITCH LEG. |
| $3a | TOGGLE SWITCH, THREE WAY TYPE, 120/277V, 20A, "a" INDICATES SWITCH LEG. |
| $4a | TOGGLE SWITCH, FOUR WAY TYPE, 120/277V, 20A, "a" INDICATES SWITCH LEG. |
| *Da | DIMMABLE SWITCH, 120/277V, 20A, "a" INDICATES SWITCH LEG. |
| a OC WG | DUAL TECHNOLOGY OCCUPANCY SENSOR, CEILING MOUNT, COVERAGE OF SENSOR DEPENDENT ON ROOM SIZE, "a" INDICATES SWITCH LEG, "WG" INDICATES WIRE GUARD INCLUDED. POWER PACKS NOT SHOWN - FIELD LOCATE AND RECORD LOCATIONS ON RECORD DRAWINGS. |
| a OC WG | DUAL TECHNOLOGY OCCUPANCY SENSOR, WALL MOUNT, COVERAGE OF SENSOR DEPENDENT ON ROOM SIZE, "a" INDICATES SWITCH LEG, "WG" INDICATES WIRE GUARD INCLUDED. POWER PACKS NOT SHOWN - FIELD LOCATE AND RECORD LOCATIONS ON RECORD DRAWINGS. |
| a OC | PIR HIGH BAY OCCUPANCY SENSOR. PROVIDE POWER PACK(S) AS REQUIRED PER MANUFACTURER'S RECOMMENDATION, "a" INDICATES SWITCH LEG. |
| J C W | 4" SQUARE BOX WITH SINGLE GANG ADAPTER FOR MOUNTING EMERGENCY LIGHTING POWER CONTROL MODULE. MOUNT WHERE INDICATED ON PLANS. PROVIDE PERMANENT LABEL ON MODULE FACEPLATE INDICATING ROOM/AREA(S) WHERE CONTROLLED LIGHTS ARE LOCATED. "C" INDICATES DEVICE FLUSH MOUNTED IN CEILING, "W" INDICATES DEVICE FLUSH MOUNTED IN WALL. FIELD COORDINATE EXACT LOCATION BEFORE ROUGH-IN. |
| *F 135° | ADDRESSABLE FIRE ALARM HEAT DETECTOR. CEILING MOUNT COMBINATION RATE-OF-RISE (15 DEGREES F PER MINUTE) AND/OR FIXED TEMPERATURE (135 DEGREES F) AS NOTED IN SPECIFICATION 284621.11. ASTERISK "*" = VANDALPROOF STYLE DEVICE GUARD. |
| S *P | ADDRESSABLE FIRE ALARM PHOTOELECTRIC SMOKE DETECTOR. CEILING MOUNT. ASTERISK "*" = VANDALPROOF (PERFORATED) STYLE DEVICE COVER, REFER TO DETAIL #3, DRAWING E8.4. |
| S *P | ADDRESSABLE FIRE ALARM PHOTOELECTRIC SMOKE DETECTOR. WALL MOUNT ON RECESSED DEVICE BOX. ASTERISK "*" = VANDALPROOF (PERFORATED) STYLE DEVICE COVER, REFER TO DETAIL #3, DRAWING E8.4. |
| S D | ADDRESSABLE FIRE ALARM DUCT MOUNTED SMOKE DETECTOR, HOUSING, AND SAMPLING TUBE ON RETURN SIDE. INTERLOCK WITH DAMPER/FAN MOTOR CONTROL TO SHUTDOWN AIR HANDLING UNIT UPON DETECTION. PROVIDE AND WIRE AN ILLUMINATED REMOTE TEST SWITCH INTERLOCKED TO THE EQUIPMENT; CENTRALLY LOCATE IN WORK C2003, LOCATION SHALL BE READILY ACCESSIBLE TO FIREMEN FOR SMOKE MANAGEMENT CONTROL. |
| RTS | ILLUMINATED REMOTE TEST SWITCH INTERLOCKED TO SHUTDOWN AIR HANDLING EQUIPMENT AS "SIMULATED TEST" OF DUCT SMOKE DETECTOR ACTIVATION AND AHU SHUTDOWN BY IAM INTERLOCK. CENTRALLY LOCATE IN WORK C2003, LOCATION SHALL BE READILY ACCESSIBLE TO FIREMEN FOR SMOKE MANAGEMENT CONTROL |
| F WP * | NON-ADDRESSABLE FIRE ALARM HORN. REFER TO DETAIL #1, DRAWING E8.4 FOR DEVICE MOUNTING HEIGHT. WP = WEATHERPROOF STYLE DEVICE. ASTERISK "*" = VANDALPROOF STYLE DEVICE GUARD. |
| F WP * | NON-ADDRESSABLE FIRE ALARM HORN WITH VISUAL/SYNCHRONIZED STROBE. REFER TO DETAIL #1, DRAWING E8.4 FOR DEVICE MOUNTING HEIGHT. WP = WEATHERPROOF STYLE DEVICE. ASTERISK "*" = VANDALPROOF STYLE DEVICE GUARD. |
| F S * | NON-ADDRESSABLE FIRE ALARM VISUAL/SYNCHRONIZED STROBE. REFER TO DETAIL #1, DRAWING E8.4 FOR DEVICE MOUNTING HEIGHT. ASTERISK "*" = VANDALPROOF STYLE DEVICE GUARD. |
| F * | ADDRESSABLE FIRE ALARM MANUAL PULL STATION. REFER TO DETAIL #1, DRAWING E8.4 FOR DEVICE MOUNTING HEIGHT. ASTERISK "*" = VANDALPROOF STYLE DEVICE COVER. |
| FAAP | REMOTE FIRE ALARM ANNUNCIATOR PANEL. REFER TO DETAIL #1, DRAWING E8.4 FOR DEVICE MOUNTING HEIGHT. |
| FACP | FIRE ALARM CONTROL PANEL. REFER TO DETAIL #1, DRAWING E8.4 FOR DEVICE MOUNTING HEIGHT. |
| FA-GAP | FIRE ALARM/DETECTION GRAPHIC ANNUNCIATOR WORKSTATION AND PRINTER. |
| FA-NAC | FIRE ALARM/DETECTION REMOTE NOTIFICATION APPLIANCE CABINET. |
| BF | FIRE ALARM MONITOR POINT, BACKFLOW PREVENTER/PRESSURE INDICATING SWITCH. |
| TS WP | FIRE ALARM MONITOR POINT, TAMPER SWITCH. WP = WEATHERPROOF STYLE DEVICE. |
| FS | FIRE ALARM MONITOR POINT, FLOW SWITCH. |
| IAM WP | FIRE ALARM INTERMEDIATE ADDRESSABLE MODULE. IAM LOOP POWERED BY FACP (SEPARATE POWER SUPPLY NOT REQUIRED UNLESS OTHERWISE INDICATED BY MFR). WP = WEATHERPROOF STYLE DEVICE. |
| ZAM WP | FIRE ALARM ZONE ADDRESSABLE MODULE. WP = WEATHERPROOF STYLE DEVICE. |
| VESDA | VERY EARLY SMOKE DETECTION APPARATUS ALARM/MONITORING PANEL (SUITABLE UP TO 40 PORTS). |
| SD SD | "VESDA" SMOKE DETECTION, REFER TO SPECIFICATION 284621.11 FOR DETAILED REQUIREMENTS. DEDICATED TUBE FOR EACH SAMPLING PORT/DETECTOR. |
| S *H | FIRE ALARM PHOTOELECTRIC SMOKE DETECTOR WITH OUTPUT CONTACTOR FOR CONNECTION TO FIRE ALARM DOOR HOLD OPEN, CEILING MOUNT. ASTERISK "*" = VANDALPROOF STYLE DEVICE COVER. |
| F/SD | FIRE AND SMOKE DAMPER. REFER TO DETAIL #6 ON DRAWING M5.2 FOR SMOKE DAMPER CONTROL DIAGRAM AND DETAILS #1 AND #2 ON DRAWING M7.2 FOR SMOKE EXHAUST MANAGEMENT CONTROL SCHEMATICS. |
| CO | CARBON MONOXIDE GAS DETECTION SENSOR (FURNISHED AND INSTALLED BY DIVISION 23). |
| NO2 | NITROGEN DIOXIDE GAS DETECTION SENSOR (FURNISHED AND INSTALLED BY DIVISION 23). |
| HLI | HIGH-LEVEL INTERFACE BOX FOR VESDA COMMUNICATION NETWORK, LOCATED ADJACENT TO EACH AIR SAMPLING SMOKE DETECTOR ALARM/MONITORING PANEL. (OR ALTERNETIVELY WHERE FACP COMMUNICATIONS PROTOCOL(S) DO NOT SUPPORT THE VESDA COMMUNICATIONS PROTOCOL NETWORK, PROVIDE ZAM(S) AT EACH VESDA AIR SAMPLING SMOKE DETECTOR ALARM/MONITORING PANEL FOR ALARM/INGMONITORING AS NOTED IN SPECIFICATION SECTION 284621.11 AND/OR AS OTHERWISE NOTED). |
| PWR | POWER SUPPLY CABINET WITH BATTERY CHARGER/BATTERIES (120VAC INPUT POWER, 24VDC OUTPUT POWER). LOCATED ADJACENT TO EACH VESDA AIR SAMPLING SMOKE DETECTOR ALARM/MONITORING PANEL. |
| ANSUL | KITCHEN HOOD FIRE SUPPRESSION MONITOR POINT. REFER TO 'FS' FOOD SERVICES DRAWINGS FOR ANSUL CABINET LOCATION AND DETAILED WIRING REQUIREMENTS. |
| PIV | POST INDICATOR VALVE MONITOR POINT, VALVE POSITION. |
| DH | FIRE ALARM DOOR HOLD OPEN DEVICE. |
| FD | SMOKE DAMPER. CONNECT TO LEGALLY REQUIRED 120VAC BRANCH CIRCUIT. DAMPER SHALL OPEN UPON ENERGIZATION (OR FAIL CLOSED UPON DE-ENERGIZATION). POWER TO SMOKE DAMPER(S) ASSOCIATED WITH AHU SHALL BE CONTROLLED BY THE FIRE ALARM CONTROL PANEL - I.E. THE 120VAC CIRCUIT SHALL BE WIRED VIA DRY, FORM C ISOLATION CONTACT (IN THE IAM). UPON DUCT DETECTOR SMOKE DETECTION AT AHU, ASSOCIATED DAMPER(S) SHALL CLOSE (BE DE-ENERGIZED). REFER TO DETAIL #5 ON DRAWING E8.4 FOR SMOKE DAMPER WIRING DETAIL. REFER TO DRAWINGS E2.3 AND E4.X SERIES FOR LOCATIONS OF AHU(S) REQUIRING DUCT SMOKE DETECTOR(S). |
| P | 4"x4" EXTRA DEEP WIERING DEVICE BOX WITH A BLANK FACEPLATE IN THE WALL FOR USE AS A PULL BOX FOR DATA CABLES. INSTALL WIRING DEVICE BOX (PULL BOX) AT +16" AFF, UON. |
| | 4-GANG FLUSH FLOOR BOX WITH TWO (2) OF FOUR (4) GANGS FOR DATA AND TWO (2) OF FOUR (4) GANGS FOR POWER. BOX TO BE PROVIDED WITH DIVIDER TO SEPARATE POWER AND DATA CABLING. PROVIDE SIX (6) CAT 6 OUTLETS AND SIX (6) CAT 6 CABLES UON. ROUTE 1-1/4"C (EMT) [FOR DATA OUTLETS] IN WALL AND STUBBED OUT AT CEILING WITH A BUSHING; PROVIDE A 4"x4" EXTRA DEEP WIRING DEVICE BOX WITH A BLANK FACEPLATE IN THE WALL FOR USE AS A PULL BOX (INSTALL PULLBOX [WIRING DEVICE BACKBOX] AT +16" AFF, UON). FOR FLUSH FLOOR BOX DETAIL, REFER TO DETAIL 7 ON DRAWING E8.5. |
| * | COMBINATION CAT 6 TELEPHONE (VOIP)/DATA 2-PORT SINGLE GANG OUTLET. FOR EACH DEVICE 1-DATA/1-TELEPHONE (VOIP) JACK WITHIN THAT MUTOA. INSTALL WITHIN A 4" x 4" EXTRA DEEP BOX WITH ADAPTER FOR SINGLE GANG PLATE. PROVIDE TWO (2) CAT 6 CABLES. INSTALL DEVICE WITH BOTTOM AT +16" AFF., UON. ASTERISK "*" = VANDALPROOF STYLE DEVICE FACEPLATE. |
| T * IP | CAT. 6 TELEPHONE (VOIP) 1-PORT SINGLE GANG OUTLET. PROVIDE A WALL TELEPHONE FACEPLATE WITH MOUNTING STUDS FOR PROVIDING PHONE HANDSET ON FACEPLATE. PROVIDE ONE (1) CAT 6 CABLE INSTALL DEVICE AT +48" AFF., UON. ASTERISK "*" = VANDALPROOF STYLE DEVICE FACEPLATE. IP = INMATE PHONE, T = TELEPHONE |
| *TCS | TABLET CHARGING STATION, SINGLE GANG 2-PORT DATA OUTLET. FOR EACH DEVICE 2-DATA/TELEPHONE (VOIP) JACKS WITHIN THAT MUTOA. INSTALL WITHIN A 4" x 4" EXTRA DEEP BOX. PROVIDE TWO (2) CAT 6 CABLES. COORDINATE EXACT LOCATION WITH OWNER PROVIDED EQUIPMENT. ASTERISK "*" = VANDALPROOF STYLE DEVICE FACEPLATE |
| *PROJ | ONE (1) HDMI 2.1 INTERFACE OUTLET AND ONE (1) USB 3.1 INTERFACE OUTLET FOR USE AS INPUTS TO OVERHEAD CEILING PROJECTOR. PROVIDE 4" x 4" EXTRA DEEP BOX WITH ADAPTER RING FOR SINGLE GANG FACEPLATE; ROUTE 1-1/4"C (EMT) UP ABOVE CEILING AND STUBBED OUT AT CEILING WITH A BUSHING. FURNISH AND INSTALL PRE-TERMINATED HDMI 2.1 CABLE BETWEEN HDMI INTERFACES WITHIN ROOM AS INDICATED ON PLANS. FURNISH AND INSTALL PRE-TERMINATED USB 3.1 CABLE BETWEEN USB 3.1 INTERFACES WITHIN ROOM AS INDICATED ON PLANS. INSTALL WIRING DEVICE BOX WITH BOTTOM AT +16" AFF, U.O.N. ASTERISK "*" = VANDALPROOF STYLE DEVICE FACEPLATE. |
| PROJ | OVERHEAD CEILING PROJECTOR (BY OWNER). PROVIDE ONE (1) HDMI 2.1 INTERFACE OUTLET, ONE (1) USB 3.1 INTERFACE OUTLET, ONE (1) COAXIAL TV OUTLET, AND ONE (1) CAT 6 OUTLET. PROVIDE 4" x 4" EXTRA DEEP BOX WITH ADAPTER RING FOR SINGLE GANG FACEPLATE; INSTALL WIRING DEVICE BOX FLUSH WITH CEILING AND LOCATED ADJACENT TO PROJECTOR. FURNISH AND INSTALL PRE-TERMINATED HDMI 2.1 CABLE BETWEEN HDMI INTERFACES WITHIN SAME ROOM AS INDICATED ON PLANS. UON. FUNISH AND INSTALL PRE-TERMINATED USB3.1 CABLE BETWEEN USB INTERFACES WITHIN SAME ROOM AS INDICATED ON PLAN UON. USE ONE (1) 1-1/4"C (EMT) FOR HDMI2.1 CABLE/USB 3.1 CABLE. ASTERISK "*" = VANDALPROOF STYLE DEVICE FACEPLATE. |
| *USB | COMBINATION TELEPHONE (VOIP)/DATA 2-PORT OUTLET SINGLE GANG. FOR EACH DEVICE 1-DATA/TELEPHONE (VOIP) JACK AND 1-USB 3.1 JACK WITHIN THAT MUTOA. INSTALL WITHIN A 4" x 4" EXTRA DEEP BOX WITH ADAPTER FOR SINGLE GANG PLATE. PROVIDE ONE (1) CAT 6 CABLE AND ONE (1) USB 3.1 CABLE UON. INSTALL DEVICE WITH BOTTOM AT +16" AFF., UON. ASTERISK "*" = VANDALPROOF STYLE DEVICE FACEPLATE |
| *TV | COMBINATION TELEVISION/DATA 2-PORT OUTLET SINGLE GANG. FOR EACH DEVICE 1-DATA/1-TELEVISION JACK WITHIN THAT MUTOA. INSTALL WITHIN A 4" x 4" EXTRA DEEP BOX WITH ADAPTER FOR SINGLE GANG PLATE. PROVIDE ONE (1) CAT 6 CABLE AND ONE (1) COAX CABLE. INSTALL DEVICE AT +84" AFF., UON ASTERISK "*" = VANDALPROOF STYLE DEVICE FACEPLATE. |
| *HD/TV | ONE (1) HDMI 2.1 INTERFACE OUTLET, ONE (1) (COAXIAL TV OUTLET), AND ONE (1) CAT 6 OUTLET. PROVIDE 4" x 4" EXTRA DEEP BOX WITH ADAPTER RING FOR SINGLE GANG PLATE AND ROUTE ONE (1) 1-1/4"C (EMT) CONDUIT SLEEVE FROM BOX TO UP ABOVE CEILING AND STUBBED OUT AT CEILING WITH BUSHING. FURNISH AND INSTALL PRE-TERMINATED HDMI 2.1 CABLE BETWEEN INTERFACES WITHIN ROOM AS INDICATED ON PLANS. COORDINATE LOCATION WITH EQUIPMENT ON SITE. INSTALL DEVICE WITH BOTTOM AT +16" AFF., U.O.N ASTERISK "*" = VANDALPROOF STYLE DEVICE FACEPLATE. |
| * | ONE (1) HDMI 2.1 INTERFACE OUTLET AND TWO (2) CAT 6 OUTLETS. PROVIDE 4" x 4" EXTRA DEEP BOX WITH ADAPTER RING FOR SINGLE GANG FACEPLATE; ROUTE ONE (1) 1-1/4"C (EMT) CONDUIT SLEEVE FROM BOX TO UP ABOVE CEILING AND STUBBED OUT AT CEILING WITH A BUSHING. FURNISH AND INSTALL PRE-TERMINATED HDMI 2.1 CABLE BETWEEN HDMI INTERFACES WITHIN ROOM AS INDICATED ON PLANS. INSTALL WIRING DEVICE BOX WITH BOTTOM AT +16" AFF, U.O.N. ASTERISK "*" = VANDALPROOF STYLE DEVICE FACEPLATE. |
| *VV | VIDEO VISITATION DATA OUTLET, SINGLE GANG. INSTALL A 4" x 4" EXTRA DEEP BOX WITH ADAPTER FOR SINGLE GANG PLATE AND BLANK COVER, PROVIDE WITH SECURITY FASTENERS ON COVER. PROVIDE ONE (1) 3/4" CONDUIT WITH PULLSTRING FROM BOX UP WALL AND STUBBED OUT INTO CHASE AREA BEHIND DAYROOM/CELLS FOR FUTURE CABLING. MOUNT BOX AT +48" AFF., UON ASTERISK "*" = VANDALPROOF STYLE DEVICE FACEPLATE. |
| POTS | PLAIN OLD TELEPHONE SYSTEM OUTLET. PROVIDE (1) CAT 6 CABLE WITH (1) RJ11 JACK AND SINGLE GANG BOX. INSTALL DEVICE WITH BOTTOM AT +16" AFF., U.O.N |
| WAP * | POE WIRELESS ACCESS POINT (WAP). PROVIDE TWO (2) CAT 6A CABLES PER IEEE 802.11ac. CEILING MOUNT AND/OR SURFACE/FLUSH MOUNT AS INDICATED ON DRAWINGS. ASTERISK "*" = CUSTOM VANDALPROOF, NON METALLIC COVER. |
| | CONDUIT CONCEALED IN GROUND OR FLOOR U.O.N. |
| | CONDUIT TURN UP AND TURN DOWN RESPECTIVELY. |
| A L1# a N.L. | LIGHT FIXTURE. "A" INDICATES FIXTURE TYPE. "a" INDICATES SWITCH LEG. "L1#" INDICATES CIRCUIT NUMBER FIXTURE IS CONNECTED TO. REFER TO LIGHTING FIXTURE SCHEDULE ON DRAWING E6.1. N.L. = FIXTURE WITH BUILT-IN NIGHT LIGHT. |
| A L1# a N.L. EM | LIGHT FIXTURES WITH HALF SOLID SHADING INDICATES FIXTURE IS USED FOR EMERGENCY EGRESS LIGHTING. "A" INDICATES FIXTURE TYPE. "a" INDICATES SWITCH LEG. "L1#" INDICATES CIRCUIT NUMBER FIXTURE IS CONNECTED TO. N.L. = NIGHT LIGHT, CONTINUOUS OPERATION; NON-CONTROLLED. EM = FIXTURE SUPPLIED WITH EMERGENCY LIGHTING POWER CONTROL MODULE, CONTROLLED. REFER TO LIGHTING FIXTURE SCHEDULE ON DRAWING E6.1. |
| PC | PHOTOCELL |
| | DISTRIBUTION PANELBOARD, SEE PANELBOARD SCHEDULES FOR DETAILED REQUIREMENTS. |
| | PANELBOARD, SEE PANELBOARD SCHEDULES FOR DETAILED REQUIREMENTS. |
| | NON-FUSED DISCONNECT SWITCH. SEE DRAWINGS AND ELECTRICAL CONNECTION SCHEDULE ON DRAWING E6.2 FOR DETAILED REQUIREMENTS. |
| | FUSED DISCONNECT SWITCH, SEE DRAWINGS AND ELECTRICAL CONNECTION SCHEDULE ON DRAWING E6.2 FOR DETAILED REQUIREMENTS. |
| | NON-COMBINATION STARTER, SEE DRAWINGS AND ELECTRICAL CONNECTION SCHEDULE ON DRAWING E6.2 FOR DETAILED REQUIREMENTS. |
| 3 | COMBINATION FULL VOLTAGE NON-REVERSING (FVNR) MAGNETIC MOTOR STARTER WITH DISCONNECT, NUMBER INDICATES NEMA RATING, SIZE 1 UON. SEE DRAWINGS AND ELECTRICAL CONNECTION SCHEDULE ON DRAWING E6.2 FOR DETAILED REQUIREMENTS. |
| | VARIABLE FREQUENCY DRIVE, SEE DRAWINGS AND ELECTRICAL CONNECTION SCHEDULE ON DRAWING E6.2 FOR DETAILED REQUIREMENTS. |
| | VARIABLE FREQUENCY DRIVE AND DISCONNECT COMBINATION, SEE DRAWINGS AND ELECTRICAL CONNECTION SCHEDULE ON DRAWING E6.2 FOR DETAILED REQUIREMENTS. |
| 3 | NON-COMBINATION FULL VOLTAGE NON-REVERSING (FVNR) MAGNETIC MOTOR STARTER NUMBER INDICATES NEMA RATING, SIZE 1 U.O.N. SEE DRAWINGS AND ELECTRICAL CONNECTION SCHEDULE ON DRAWING E6.2 FOR DETAILED REQUIREMENTS. |
| $*M | 125VAC, 20A, 1P MOTOR RATED TOGGLE SAFETY DISCONNECT WITH RED (ENERGIZED) LED PILOT LIGHT AND THERMAL OVERLOAD UON. ASTERISK "*" = VANDALPROOF STYLE DEVICE FACEPLATE. |
| | MOTOR. |
| PB * | PULLBOX<br>ASTERISK "*" = VANDALPROOF STYLE DEVICE |
| | BUILDING OR TELECOM GROUND BUS BAR. REFER TO DETAILS #1, #2 , #3 AND #5 ON DRAWING E8.3. |
| GAA | REMOTE GENERATOR ALARM ANNUNCIATOR PANEL. |
| | OVERHEAD DOOR SAFETY INTERLOCKS. REFER TO SPECIFICATION SECTIONS 083323 AND 083613 FOR MORE INFORMATION. DEVICES PROVIDED BY DOOR VENDOR AND INSTALLED AND WIRED BY CONTRACTOR. |
| | LOCAL KEYED OPEN-STOP-CLOSE OVERHEAD DOOR PUSHBUTTON CONTROL STATION. REFER TO SPECIFICATION SECTIONS 083323 AND083613 FOR MORE INFORMATION. INSTALL DEVICE AT +48" AFF UON. DEVICES PROVIDED BY DOOR VENDOR AND INSTALLED AND WIRED BY CONTRACTOR. |
| | CONTROL STATION (TYPE AS INDICATED ON DRAWINGS; I.E. OPEN-STOP-CLOSE OVERHEAD DOOR, ADA DOOR OPENER, ETC.). MOUNTING HEIGHT AS INDICATED ON DRAWINGS. CONTROL STATION PROVIDED BY CONTROLLED DEVICE VENDOR AND INSTALLED AND WIRED BY CONTRACTOR. |
| E | LOW VOLTAGE ELECTRICAL CONNECTION TO AUTOMATIC FLUSH VALVE AND/OR AUTOMATIC WATER FAUCET VALVE. REFER TO POWER PLANS AND DETAIL #1 ON DRAWING E8.1. |
| T | LOW VOLTAGE TRANSFORMER (I.E. FOR POWERING AUTOMATIC FLUSH VALVE AND/OR AUTOMATIC WATER FAUCET VALVE). REFER TO POWER PLANS AND DETAIL #1 ON DRAWING E8.1. |
| FFSCP | FIREFIGHTER SMOKE CONTROL PANEL. |
| | BRANCH CIRCUIT HOME-RUN SYMBOLOGY:<br>SOLID CIRCLE INDICATES GROUND CONDUCTOR<br>LONG LINE INDICATES NEUTRAL CONDUCTOR(S)<br>SHORT LINE INDICATES PHASE CONDUCTOR(S) |

## ONE-LINE DIAGRAM SYMBOLS:

| | |
|---|---|
| PANEL 200 AMP 120/208V 3Ø, 4W MLO | MAIN LUG ONLY PANELBOARD. "PANEL" INDICATES PANEL DESIGNATION. "120/208" INDICATES PANEL OPERATING VOLTAGE. "3Ø, 4W" INDICATES PHASE AND WIRE. "200A 3P" INDICATES 3 POLE MAIN LUGS AND BUS RATED FOR 200A. |
| PANEL 200 AMP 120/208V 3Ø, 4W MCB | MAIN CIRCUIT BREAKER PANELBOARD. "PANEL" INDICATES PANEL DESIGNATION. "120/208" INDICATES PANEL OPERATING VOLTAGE. "3Ø, 4W" INDICATES PHASE AND WIRE. "200A 3P" INDICATES 3 POLE MAIN LUGS AND BUS RATED FOR 200A. |
| 200 AT 200 AF | FUSED SWITCH. TOP NUMBER INDICATES SWITCH RATING IN AMPERES. BOTTOM NUMBER INDICATES FUSE RATING IN AMPERES. |
| 200AT 200AF 80% RATED LSIG SS | MOLDED CASE THERMAL MAGNETIC CIRCUIT BREAKER. TOP NUMBER INDICATES TRIP RATING IN AMPERES. BOTTOM NUMBER INDICATES FRAME RATING IN AMPERES. "80% RATED" INDICATES BREAKER RATING. "LSIG" INDICATES BREAKER WITH ADJUSTABLE LONG TIME, SHORT TIME, INSTANTANEOUS, AND GROUND FAULT TRIP SETTINGS. "SS" INDICATES SOLID STATE, 3-POLE, U.O.N. |
| | BUS BAR. |
| | FEEDER CIRCUIT. |
| 20 | MOTOR WITH HORSEPOWER INDICATED. |
| 208V 30KVA 208/120 K13 | TRANSFORMER. PRIMARY VOLTAGE, SECONDARY VOLTAGE, RATING IN KVA AS INDICATED. K FACTOR AS INDICATED. REFER TO TRANSFORMER SCHEDULE ON DRAWING E6.3 FOR DETAILED REQUIREMENTS. |
| | GROUND. |
| 100A | NON-FUSED DISCONNECT SWITCH. NUMBER INDICATES RATING IN AMPERES. |
| | ENCLOSURE OUTLINE. |
| 100 | CABLE/CONDUIT NUMBER. REFER TO CABLE AND CONDUIT SCHEDULES ON DRAWING E7.2. |
| N E L | AUTOMATIC TRANSFER SWITCH |
| SB | SWITCHBOARD |

## ABBREVIATIONS:

| | | | |
|---|---|---|---|
| A | AMPERES | MCC | MOTOR CONTROL CENTER |
| AF | AMPERE FUSE | MDF | MAIN DISTRIBUTION FRAME |
| AFC | ABOVE FINISHED COUNTER | MFR. | MANUFACTURER |
| AFF | ABOVE FINISHED FLOOR | MLO | MAIN LUG ONLY |
| AFG | ABOVE FINISHED GRADE | MOCP | MAXIMUM OVERCURRENT PROTECTION |
| AHU | AIR HANDLING UNIT | MTS | MANUAL TRANSFER SWITCH |
| AIC | AMPERES INTERRUPTING CAPACITY | MUTOA | MULTI-USER TELECOMMUNICATIONS OUTLET ASSEMBLY |
| AT | AMPERE TRIP | NAC | NOTIFICATION APPLIANCE CABINET |
| ATS | AUTOMATIC TRANSFER SWITCH | NEC | NATIONAL ELECTRICAL CODE |
| AWG | AMERICAN WIRE GAUGE | NL | NON-SWITCHED NIGHT LIGHT |
| BACnet | BUILDING AUTOMATION AND CONTROL NETWORKING PROTOCOL | NO2 | NITROGEN DIOXIDE |
| | | NO/NC | NORMALLY OPEN/NORMALLY CLOSED |
| BCT | BONDING CONDUCTOR FOR TELECOMMUNICATIONS | NTRL | NEUTRAL |
| BE | BURIED ELECTRIC | NTS | NOT TO SCALE |
| BFG | BELOW FINISH GRADE | OCP | OVERCURRENT PROTECTIVE DEVICE |
| BFO | BURIED FIBER OPTIC | OCPD | OVERCURRENT PROTECTIVE DEVICE |
| BICSI | BUILDING INDUSTRY CONSULTING SERVICES INTERNATIONAL (NOW BICSI: A TELECOMMUNICATIONS ASSOCIATION) | OL | OVERLOADS |
| | | P | POLE |
| | | PC | PERSONAL COMPUTER |
| BMS | BUILDING MANAGEMENT SYSTEM | PCM | (EMERGENCY) POWER CONTROL MODULE |
| BSMT. | BASEMENT | PH | PHASE |
| BT | BURIED TELEPHONE | PIR | PASSIVE INFRARED |
| C. | CONDUIT | PIV | POST INDICATE VALVE |
| CAT | CATEGORY | POE | POWER OVER ETHERNET |
| CATV | CABLE TELEVISION/COMMUNITY ANTENNA TELEVISION | POTS | PLAIN OLD TELEPHONE SYSTEM |
| | | Ø | PHASE |
| CB | CIRCUIT BREAKER | RCDD | BICSI REGISTERED COMMUNICATIONS DISTRIBUTION DESIGNER |
| CU | COPPER | RCPT | RECEPTACLE |
| CVC | CELL VALVE CONTROLLER | | |
| DED | DEDICATED | RECEPT | RECEPTACLE |
| DFA | DROP FROM ABOVE | RFID | RADIO FREQUENCY INDENTIFICATION |
| DIV. | DIVISION | RLA | RUNNING LOAD AMPERES |
| D.S | DISCONNECT SWITCH | RM | ROOM |
| E.T.R. | EXISTING TO REMAIN | RTU | ROOF TOP UNIT |
| EX | EXISTING TO REMAIN | SE | SERVICE ENTRANCE |
|